

HXSP-2108F USB 2.0 To RS-485 Converter



Specification & Features:

USB specification revision 1.1 & 2.0 compliant.
Small volume, easy installation
No power supply needed.
Auto sense serial signal rate, zero delay automatic transmit
Baud rate: 300~115200bps, automatic sense serial signal rate
.....

Introduction:

HXSP-2108F provides a simple and easy way to connect Universal Serial Bus(USB) and Serial port interface, With the advantage of USB port, user have the capability to utilize the peripheral with serial port interface in an easy to use environment such as plug and play & hot swap function, This adapter is designed for ideal connections to Cellular phone, Digital Camera, modems or ISDN terminal adapter with over 1Mbps data transfer rate.

Detail Specification & Features:

USB specification revision 1.1 & 2.0 compliant.
Small volume, easy installation
No power supply needed.
Auto sense serial signal rate, zero delay automatic transmit
Baud rate: 300~115200bps, automatic sense serial signal rate
Transmit distance reach up to 1800M at the rate of 9.6kbps
Protection: 600W surge protection, 15KV static electricity protection
Connector: USB side type A interface female, RS-485 side DB-9 male or 6 terminal block
Working temperature: -20 to 60 centigrade